



Power in ■ Load Output

934112 Electronic Timer

SPECIFICATIONS

7 Day timer, 24 Hrs
 Programming: 7-day, up to 16-settings
 Manual-Auto Switch
 Power and status LED
 Battery backup 3 years

Operating voltage 110VAC
 Resistive 25 Amp
 Ballast 10 Amp
 Motor 1 HP

To replace the battery click down the RED clip and remove the unit, on the back side is the battery compartment replace the AA battery

To set the current time: (Military time 24 Hrs)
 Hold down the CLOCK key and adjust the respectively key HOUR, MINUTE and WEEK

Event setting:

- 1 Press TIMER key shows display 1 ON
- 2 Press the HOUR key set the on time, Press MINUTE key select ,
- 3 press WEEK key select days,
- 4 Press TIMER again shows display OFF,
- 5 Press the HOUR key set the on time, Press MINUTE key select ,
- 6 press WEEK key select days, to end press CLOCK

To add another event repeat steps 1 to 6

To check your program press the TIMER key

For manual or auto operation use the AUTO-MANUAL key the display ▼ will show the status ON MANUAL OFF

NOTE on any error press the RESET key